

I、 Introduction

1. No UV, IR or other deleterious radiation
2. Vivid emitting color
3. Can be replaced G12 with tradition
4. Energy saving and safety

II、 Parameter

1. LED Emitting Color: Warm white
2. Voltage: AC200-240V
3. Lifetime: >30, 000 hours
4. Power: 10W



III、 Electro - Optical

| Parameter | Symbol | Min | | Max | Unit |
|-----------------------|--------|-----|------|------|------|
| Brightness | Flux | | 800 | | lm |
| Color Temperature | CCT | | 2700 | 3200 | K |
| Voltage | V / AC | 200 | | 240 | V |
| Operation Temperature | To | -25 | 30 | 50 | °C |
| Total Power | P | | 10 | | W |

IV、 Size (Unit: mm)

